

SBE® 160 / SBX® 175 Connectors

Up to 280 Amps



SBX° and SBE° connectors can integrate up to 8 auxiliary power / signal contacts along with the two primary power circuits. SBE° connectors feature an IEC 60950 touch safe housing molded from a chemical resistant PBT / PC blend resin. SBX° are molded from a rugged PC resin and are rated IP20 per IEC 60529.

- Meets EN1175:2020
- Touch Safe Interface
 Minimizes potential contact with live circuits per IEC 60950
 & IEC 60529
- Up to 8 Last Mate / First Break Auxiliaries
 Enables intelligent power switching, CAN and interlock loop
 circuitry, as well as power up to 20 amps per pole
- Color-coded Mechanical Voltage Keys
 Like all Multipole connectors, the SBE® and SBX® offer an
 easy way to identify circuits and protect against cross mating


SBE® 160 / SBX® 175 ORDERING INFORMATION

SBE® 160 / SBX® 175 Housings

The middle size of SBE®, X, O style housing. SBE® housings are molded from a chemical resistant PBT. SBX® housings are molded from PC. SBE® 160 and SBX® 175 housings of the same Voltage Color-Code can be mated (except yellow) but is not recommended as it invalidates UL approvals. SBX® 175 housings do not meet EN1175:2020 requirements for industrial trucks.

| Description | SBE® 160 Part Numbers | | s SBX® 175 Part Numb | |
|------------------|-----------------------|---------|----------------------|--------|
| Minimum Quantity | 100 | 25 | 100 | 25 |
| Yellow | 2-8170G4 | E6383G1 | 2-7251G4 | 6383G1 |
| Orange | 2-8170G3 | E6382G1 | 2-7251G3 | 6382G1 |
| Red | 2-8170G5 | E6385G1 | 2-7251G5 | 6385G1 |
| Gray | 2-8170G1 | E6380G1 | 2-7251G1 | 6380G1 |
| Blue | 2-8170G2 | E6381G1 | 2-7251G2 | 6381G1 |
| Green | 2-8170G7 | E6390G1 | 2-7251G7 | 6390G1 |
| Black | 2-8170G14 | E6392G1 | N/A | N/A |

 $^{^{\}star}$ Yellow SBE $^{\rm B}$ 160 and SBX $^{\rm B}$ 175 housings are NOT intermateable.




SBE® 160 / SBX® 175 Silver Plated Primary Power Wire Contacts

Use two silver plated contacts per housing for the best electrical performance and durability up to 10,000 mating cycles. See reducing bushings in accessory section for smaller wires.

| | | | Dimen | |
|---------------------|-------------|--------------|--------|------|
| AWG mm ² | Loose Piece | Part Numbers | inches | mm |
| Minimum Quantity | 500 | 50 | | |
| 1/0 50 | 6384G1-BK | 6384G1 * | 0.44 | 11.1 |
| 2 35 | 6384G2-BK | 6384G2 * | 0.38 | 9.7 |








^{*} Sold as pairs. 2 parts shipped for every 1 part ordered.

$SBE^{\$}~160~/~SBX^{\$}~175~CONNECTOR~TEMPERATURE~CHARTS~-$ Temperature rise charts are based on a 25°C ambient temperature.

Current - Temperature Derating per IEC 60512-5-2 Test 5B







| EN1175:2020 Rating | | | |
|---------------------------------------------|----|--|--|
| Rated Current Cable cross-section (A) (mm²) | | | |
| 160 | 35 | | |

SBE® 160 / SBX® 175 CONNECTOR SPECIFICATIONS

| ELECTRICAL SBE® 160 / SBX® 175 Connectors - Up to 280A | | | | | |
|------------------------------------------------------------|---------------------|-------|-------------|--|--|
| Electrical | SBE® / SBX® SBE® On | | SBE® Only | | |
| Current Rating Amperes ¹ | USR | CNR | EN1175:2020 | | |
| Primary Power (1/0) | 280 | 175 | 160 | | |
| Powerpole® Auxiliary | 20 | 20 | N/A | | |
| 1x4 Auxiliary (12 AWG) | 20 | 20 | N/A | | |
| PPMX Auxiliary (20 AWG) | 7 | 5 | N/A | | |
| Voltage Ratings | | | | | |
| Primary Power Contact | 600 | 600 | 150 | | |
| Powerpole® Auxiliary | 600 | 600 | 150 4 | | |
| 1x4 Auxiliary (12 AWG) | 600 | 600 | N/A | | |
| Dielectric Withstanding Voltage | | | | | |
| Volts AC | 2,200 | 2,000 | 2,000 | | |
| Avg. Mated Contact Resistance 1 | | | | | |
| 6" of 1/0 AWG Wire | 0.1 | 0.1 | | | |
| UL Hot Plug Current Rating Amperes - 250 Cycles at 120V DC | | | | | |
| Power | 100 | 100 | | | |
| Powerpole® Auxiliary | 30 | 30 | | | |
| 1x4 Auxiliary | 5A | 5A | | | |

| Specifications | continued | l on | next | page |
|----------------|-----------|------|------|------|
|----------------|-----------|------|------|------|

| MATERIALS | |
|-----------------------------------|------------------------------------|
| Housing | |
| SBX® and Powerpole® Plastic Resin | Polycarbonate |
| SBE® and 1x4 Auxiliary Housing | Polycarbonate / PBT Blend |
| Contact Retention Spring | Stainless Steel |
| Housing Flammability Rating | |
| UL94 | V-0 |
| Glow Wire - SBE® 160 Only | 960°C (GWFI) / 850°C (GWIT) |
| Power & Powerpole® Contact | Silver Plated Copper Alloy |
| 1x4 Auxiliary Contacts | |
| Pin | Copper Alloy, Au Over Ni |
| Socket | BeCu, Au Over Ni |
| Socket Body | Copper Alloy, Sn Bright Over Ni |
| Retention Clip | Stainless Steel |
| PPMX Contacts | Gold Plated Copper Alloy |
| Contact Termination Methods | |
| Crimp ³ | |
| Hand Solder | |

| MECHANICAL | | |
|---------------------------------------|-------------|--------------|
| Wire Size Range | AWG | mm² |
| Power Contacts | 10 to 1/0 | 5.3 to 53.5 |
| Auxiliary Contacts | 24 to 10 | 0.25 to 5.3 |
| Max. Wire Insulation Diameter | in. | mm |
| Power Contacts | 0.600 | 15.200 |
| Powerpole® Auxiliary | 0.175 | 4.450 |
| 1x4 Auxiliary | 0.140 | 3.600 |
| Operating Temperature ² | °F | °C |
| SBX® and SBE® Housings | -4° to 221° | -20° to 105° |
| Mating Cycles No Load by Plating | Silver (Ag) | Gold (Au) |
| Power Contacts | 10,000 | |
| Powerpole® Auxiliary | 10,000 | |
| 1x4 Auxiliary | | 10,000 |
| PPMX Auxiliary | | 5,000 |
| Avg. Mating / Unmating Force | Lbf. | N |
| Main Connector Housing | 30 | 134 |
| Per Powerpole® Connector | 5.00 | 22.00 |
| Per Contact in 1x4 Auxiliary | 0.70 | 3.00 |
| Per PPMX Housing | 4.50 | 20.00 |
| Min. Contact / Spring Retention Force | Lbf. | N |
| Power Standard Housing | 120 | 533.7 |
| Powerpole® Housing | 25 | 111 |
| 1x4 Auxiliary Housing | 10 | 44.5 |
| PPMX Housing | 12 | 53 |







NOTE 1: See IEC 60664-1 for working voltage.

NOTE 2: Amp ratings are stated per position and based on all positions being fully loaded.

- 1 Based on: 105°C rated or better cable of the largest size. Properly calibrated Anderson Power™ recommended tooling, and a 25°C ambient temperature. UL rating not to exceed the maximum operating temperature. CSA Rating below a 30°C temperature rise.
- 2 Limited by the thermal properties of the connector plastic housing.
- 3 Use Anderson Power™ recommended tooling only. Alternate tools may adversely affect the performance of our connectors along with UL and CSA recognition
- 4 Voltage capability of SBE® housing is identical to SBX®, but derated to meet EN1175:2020 requirements.

IEC INFORMATION

| Connector Series | Configurations | Creepage / Clearance per IEC 60950-1 | Material Group |
|---------------------|----------------|-----------------------------------------------|-------------------|
| SBE® 160 | Unmated | 6.1 mm | |
| CDE® 1CO | | | IIIa |

| PROTECTION | | | |
|----------------|------------------------|--------------|--|
| Touch Safety I | Main Connector Housing | | |
| IEC 60950 | SBE® 160 Only | Pass | |
| IEC 60529 | SBE® 160 and SBX® 175 | IP20 unmated | |



| ATTRIBUTES | SBE® 160 |
|-----------------------------------------|------------------------------------------|
| AMP Rating AC/DC | 160 Amp |
| Voltage Rating AC/DC (Steady State) | 600 V AC/DC (Operational) |
| Breaking Capacity - AMP Rating / Cycles | 160 Amp / 10 Cycles |
| Voltage Rating (Breaking Capacity) | 220 VDC |
| FINGER Safety - Mated / Unmated | IEC 60529 - IP20 |
| Wire Size Tested | 50 mm² |
| Contact Series Tested | 6384G1 |
| Climatic Testing (Cold, Heat & MFG) | IEC 60512 Test -11j, 11i & 11g |
| Cycle Life | IEC 60512 Test 9a - 5,000 Cycles |
| Mechanical Strength Impact | IEC 60512-5 @ 29.5 Inchesdropped 8 times |
| Temperature Range | -20 °C to 105 °C |
| | -4 °F to 221 °F |

SBE® 160 / SBX® 175 ACCESSORIES

Cable Clamps *

Durable metal clamps adapt to a wide range of cable sizes.

| | Cable Size | | |
|----------------------------------|--------------|-------------|-------------|
| | Min / Max | Min / Max | |
| Description | Inches O.D. | mm O.D. | Part Number |
| Minimum Quantity Cable Clamp Kit | 0.62 to 0.22 | 15.7 to 5.6 | 25 945G2 |

NOTE: For assembly of clamp to housing only

The given wire O.D. information is an estimate. Cable clamps should be evaluated for performance with the actual wire to be used.




Handles are made out of durable PC plastic. Hardware to attach to connector body included in kits.

| Description | Part Numbers | |
|--------------------|--------------|-------|
| Minimum Quantity | 100 | 25 |
| Gray Handle Kit | - | 995G1 |
| Red Handle Kit | - | 995G3 |
| Handle Only, Gray | 3-5074P1 | - |
| Handle Only, Red | 3-5074P3 | - |
| Handle Only, Black | 3-5074P5 | - |
| Hardware Bag | - | 105G8 |



NOTE: For assembly of clamp to housing only




Powerpole® Auxiliary

Powerpole® auxiliary connectors are rated up to 30 amps 600 volts and can be used for auxiliary power, control or sensing. The auxiliary kit includes (1) each black and red Standard Powerpole® housing, (2) contacts, (2) zip cable straps, and (2) retaining pins. (1) Retaining clip can be Substituted for (2) retaining pins.

| Description | Part Nur | mbers |
|--------------------------|----------|-------|
| Minimum Quantity | 200 | 25 |
| Powerpole® Auxiliary Kit | - | 6344 |
| Black Powerpole® Housing | 1327G6 | - |
| Red Powerpole® Housing | 1327 | - |
| 16 to 12 AWG Contact | 1331 | - |


NOTE: Finger proof PP15/45 housings should not be used for auxiliary contacts.



1x4 Auxiliary Connector

The unique 1x4 auxiliary connector allows up to 4 auxiliary circuits up to 20 amps 150 volts each in SBE®, SBO®, & SBX® housings. The genderless design holds two each of the gold plated pin & socket contacts. This innovation allows the very durable and cost effective design of SBE®, O, X connectors to substitute for DIN 43589-1 applications where 4 auxiliary contacts are required. Multiple pin lengths allow the further benefit of sequencing between circuits. (2) Retaining pins or (1) Retaining clip is required to hold the auxiliary housing in place. Auxiliary Kits include (1) Auxiliary Housing, (2) Standard Length Pin Contacts, (2) Socket Contacts, (2) Retaining Pins and (1) Retaining Clip.

| Description | AWG | mm² | Par | t Number | S |
|-----------------------|------------|-----------------|----------|----------|-------|
| Minimum Quantity | | | 1,000 | 250 | 25 |
| 1x4 Auxiliary Kit | 12 | 4 | - | - | 441G3 |
| 1x4 Auxiliary Kit | 16 to 14 | 1.5 to 2.5 | - | - | 441G1 |
| 1x4 Auxiliary Kit | 20 to 16 | 0.75 to 1.5 | - | - | 441G2 |
| 1x4 Auxiliary Housing | Contacts S | Sold Separately | 3-5956P1 | 444G1 | - |



^{*} Torque value 30 (in - lbs) / 3.4 (Nm)

Pin Contacts for 1x4 Auxiliary Connector

Gold plated contacts are available in 4 lengths to allow sequencing of circuits.

| • | | | | | | | |
|------------------------|----------------|---------------|---------|------|------------------------|-----------------|-------------------|
| Description | AWG | mm² | | | Part | Numbers | |
| Minimum Quantity | | | | 500 | | 50 | |
| Standard Length 7.7 mm | 12 | 2.5 | | | 16P12S30 | PM16P12S30-50 | |
| | 16 to 14 | | | | 16P1416S30 | PM16P1416S30-50 | |
| | 20 to 16 | | to 1.0 | | 16P1620S30 | PM16P1620S30-50 | |
| D M + 00 | 24 to 20 | | to 0.75 | | 16P2024S30 | PM16P2024S30-50 | |
| Pre-Mate 9.3 mm | 12 16 to 14 | 2.5 1.0 to | . 1 = | | 16P12A30 16P1416A30 | - | |
| | 20 to 16 | | to 1.0 | | 16P1416A30 | - | |
| | 24 to 20 | | to 0.75 | | 16P2024A30 | - | |
| Post-Mate 6.4 mm | 12 | 2.5 | 10 0.73 | | 16P12C30 | - | |
| 1 oot mate o. 1 mm | 16 to 14 | | 15 | | 16P1416C30 | _ | Retention Clip |
| | 20 to 16 | | to 1.0 | | 16P1620C30 | _ | / (Otorialori Onp |
| | 24 to 20 | | to 0.75 | | 16P2024C30 | - | |
| | | | | | | | |
| Auxiliary Pin | | L- | -1 | .1 - | | | |
| Contact Lengths | | | | | | | - |
| | in. | mm | in. | mm | | | L |
| Standard Length 7.7 mi | m 0.77 | 19.6 | 0.30 | 7.7 | | | |
| Pre-Mate 9.3 mm | 0.83 | 21.2 | 0.37 | 9.3 | - | | |

6.4

Socket Contacts for 1x4 Auxiliary Connector

0.72


Selectively gold plated contacts offer low resistance and durability up to 10,000 mating cycles.

18.3 0.25

| Description | AWG | mm² | Part Numbers | | |
|----------------|----------|--------------|--------------|-----------------|--|
| Minimum Quanti | ty | | 500 | 50 | |
| Socket Contact | 12 | 2.5 | PM16S12S32 | PM16S12S32-50 | |
| | 16 to 14 | 1.0 to 1.5 | PM16S1416S32 | PM16S1416S32-50 | |
| | 20 to 16 | 0.75 to 1.0 | PM16S1620S32 | PM16S1620S32-50 | |
| | 24 to 20 | 0.50 to 0.75 | PM16S2024S32 | PM16S2024S32-50 | |

| Auxiliary Socket Contacts Crimp Barrel ID | | | | | | |
|--------------------------------------------|------|-----|--|--|--|--|
| Wire Gauge | in. | mm. | | | | |
| 24 to 20 | 0.04 | 1.1 | | | | |
| 20 to 16 | 0.07 | 1.7 | | | | |
| 16 to 14 | 0.08 | 2.1 | | | | |
| 12 | 0.10 | 26 | | | | |

Post-Mate 6.4 mm



[1.60] Ø 0.06


PPMX Auxiliary Connector

The PPMX auxiliary connector allows up to 8 auxiliary circuits to be used in the SBE®, SBO®, & SBX® housings. There are 4 auxiliary circuits per PPMX connector and two PPMX housings fit into the auxiliary port in the main connector housing. Rated up to 7 amps 300 volts per contact, the genderless design holds two each gold plated pin & Socket contacts. This innovation allows the very durable and cost effective design of SBE®, O, X connectors to be used for applications requiring up to 8 battery monitoring or equipment vehicle communication circuits. (2) Retaining pins or (1) Retaining clip is required to hold the auxiliary housing in place.

Auxiliary Kits includes: (1) Auxiliary Housing, (2) Pin Contacts, and (2) Socket Contacts.

| Description | AWG | mm² | Pa | rt Numbers | |
|-----------------------|----------|-----------------|-----------|------------|--------|
| Minimum Quantity | | | 1,000 | 100 | 25 |
| PPMX Auxiliary Kit | 24 to 20 | 0.50 to 0.25 | - | 4850G6 | - |
| 1x4 Auxiliary Housing | Contacts | Sold Separately | 4827G6-BK | - | 4827G6 |


^{*} No extraction tool required for contact removal.



Pin & Socket Contacts for PPMX Auxiliary Connector

Gold plated contacts are ideal for signal or low power use with durability up to 5,000 mating cycles.


| Description | AWG | mm² | Part Numbers | |
|------------------|----------|--------------|--------------|--------|
| Minimum Quantity | | | 2,000 | 50 |
| Pin Contacts | 24 to 20 | 0.50 to 0.25 | 4803G3-BK | 4803G3 |
| Socket Contacts | 24 to 20 | 0.50 to 0.25 | 4802G3-BK | 4802G3 |



SBE® Air Tubes

Air tubes fit into SBE® housings to allow electrolyte circulation while charging the battery. Genderless tube design allows the same part to be used on both sides. (2) Retaining pins or (2) Spirol pins are required to hold the air tube in place both are included in Air Tube Kit.

| Description | Part Numbers | | |
|---------------------|--------------|--------|--|
| Minimum Quantity | 500 | 25 | |
| Air Tube Kit, Black | - | 6396G1 | |
| Air Tube Only | 3-5798P1 | - | |



Retaining Clip

Retaining clips can be used in place of two retaining pins to hold auxiliary connectors or air tubes. Allows easier removal of auxiliary modules.


| Description | Part Number |
|-------------------------|-------------|
| Minimum Quantity | 100 |
| For SBE® 160 & SBX® 175 | 2-8675P2 |



Retaining Pins

Retaining pins are used to hold accessories in the auxiliary port in SBE $^{\circ}$, SBO $^{\circ}$, & SBX $^{\circ}$ housings. Dimension "B" is +/- 0.015 in or 0.38 mm.


| | | Dimensions | | | | |
|------------------------------------------|-------------------|--------------|---------------|-------------|--------|-------|
| | | | - A - | | - E | 3 - |
| Description | Part Num | nbers | inches | mm | inches | mm |
| Minimum Quantity For SBE® 160 & SBX® 175 | 1,000 110G9-BK | 100 110G9 | 0.093 / 0.099 | 2.36 / 2.51 | 0.85 | 21.59 |




Zip Cable Straps

Zip cable straps are used to secure auxiliary wires to the side of the main power cables.

| Description | Part Number |
|------------------|-------------|
| Minimum Quantity | 1,000 |
| White | H1835P3 |






Manual Release - Battery Side *

Works with the Charger / Truck side to ease mating and unmating connectors.

| Description | Part Numbers | | |
|--------------------------|--------------|-------|--|
| Minimum Quantity | 88 | 25 | |
| Bracket and Hardware Kit | - | 993G2 | |
| Battery Bracket Only | 111961P2 | - | |
| Hardware Bag | - | 105G1 | |

^{*} Torque value 30 (in - lbs) / 3.4 (Nm)

^{*}NOTE: For assembly of bracket to housing only




Manual Release - Charger / Truck Side *


Works with the Battery side to ease mating and unmating connectors.

| Description | Part Numbers | | | | |
|--------------------------|--------------|------|---|--|--|
| Minimum Quantity | 60 | 25 | | | |
| Bracket and Hardware Kit | - | 994G | 2 | | |
| Bracket / Lever Only | B00511G2 | - | | | |
| Hardware Bag | - | 105G | 1 | | |
| | | | | | |

^{*} Torque value 30 (in - lbs) / 3.4 (Nm)

^{*}NOTE: For assembly of bracket to housing only






Silver Plated Reducing Bushings: for Use with Contact Part Number 6384G1

Use with contact part number 6384G1-BK to allow a smaller wire to be used with the connector. Electrical capability is derated with smaller wire.


| Contac | cts Barrel Size | Wire | e Size | | Dimensions - ID - | | | | |
|--------|-----------------|---------|-----------|---------|----------------------|---------|------|--------|------|
| AWG | mm² | AWG | mm² | | Part Nu | mbers | | inches | mm |
| Minimu | ım Quantity | | | 1,500 | 1,000 | 500 | 100 | | |
| 1/0 | 53.5 | 1 | 42.4 | - | - | 5687-BK | 5687 | 0.39 | 9.91 |
| 1/0 | 53.5 | 2 | 33.6 | 5690-BK | - | - | 5690 | 0.34 | 8.64 |
| 1/0 | 53.5 | 4 | 21.2 | - | 5693-BK | - | 5693 | 0.27 | 6.86 |
| 1/0 | 53.5 | 6 | 13.3 | - | 5663-BK | - | 5663 | 0.22 | 5.59 |
| 1/0 | 53.5 | 10 to 8 | 5.3 - 8.4 | 5648-BK | - | - | 5648 | 0.19 | 4.83 |



Reducing Bushings: for Use with Contact Part Number 6384G2

Use with contact part number 6384G2-BK to allow a smaller wire to be used with the connector. Electrical capability is derated with smaller wire.


| Contact Barrel Size | Wire Size | Part Num | bers |
|---------------------|--------------------|----------|------|
| Minimum Quantity | | 1,000 | 100 |
| 35 mm ² | 16 mm ² | 5920-BK | 5920 |



Charger Key

Prevents charger and truck connector halves from engaging

| Description | Part Numbers | For Use With | Hardware Kit Includes | | | |
|------------------|--------------|-----------------|-----------------------|--|--|--|
| Minimum Quantity | 25 | | | | | |
| Charger Key Kit | 6337G1 | SBE®160/SBE®320 | 1 Yellow Key | | | |
| | | Connectors | 2 Retaining Pins | | | |



SBO® / SBE® / SBX® - Tooling Information

| Wi | re Size | Loose Piece Part Number | Loose Piece Contact Crimp Tools | | | | | | | | | |
|-------------------------|--------------|----------------------------|---------------------------------|-------|------------------|------|---------|---------------------|-----------|-------------|--|---------------|
| AWG | mm² | Contacts | Pneumatic Bench Tool | + | Die | + | Locator | Number of Crimps | + | Hand Tools | | |
| | | | SBE® : | 160 / | / SBX® 175 | | | | | | | |
| 1/0 | 53.5 | 6384G1 | 1387G2 | | 1303G13 | | 1304G32 | Double | | | | |
| 2 | 33.6 | 6384G2 | 1387G2 | | 1303G13 | | 1304G32 | Double | | 1368 series | | |
| 1/0 to 2 | 53.5 to 5 | 6384G1 & 6384G2 | 1387G1 | | 1388G3 | | 1389G3 | Single | | | | |
| | | F | owerpole® 15/ | 45 A | Auxiliary Contac | ts * | * | | | | | |
| 16 to 20 | 1.3 to .52 | 1332 | N/A | | N/A N/A | NI/A | Single | | 1309G2 or | | | |
| 12 to 16 | 3.3 to 1.3 | 1331 | IN/A | | | | IN/A | Sirigle | | 1309G8 | | |
| | | | PowerMod® | 1x4 / | Auxiliary Contac | cts | | | | | | |
| 12 to 24 | 3.3 to 0.20 | All Crimp Pins | TP0001* | 11* | N/A | | TL0001 | Single | | TM0001* | | |
| 12 (0 24 | 3.5 to 0.20 | All Crimp Sockets | 11 0001 | | 14/71 | | TL0002 | Sirigic | | PM1000G1 | | |
| PPMX Auxiliary Contacts | | | | | | | | | | | | |
| 20 to 24 | 0.50 to 0.25 | 4803G3 | TP0001* | | N/A | N/A | N/A | | TL0005 | Single | | TM0001* or |
| | | 4802G3 | | | | | | | | PM1000G1 | | |

Insertion / Extraction Tools

PM1002G1 - 1 x 4 Auxiliary Contact Insertion Tool - For use with PM contacts and 1x4 auxiliary housing (444G1 housings and 441G kits)

PM1003G1 - 1 x 4 Auxiliary Contact Extraction Tool - For use with PM contacts and 1x4 auxiliary housing (444G1 housings and 441G kits)

PM1003GX - 1x4 Auxiliary Contacts Inspection Tool - For use with PM contacts and 1x4 auxiliary housing (444G1 housings and 441G kits)

969P1 - SBE® 160 / SBX® 175 Power Contact Extraction Tool

970P1 - SBE® 320 / SBX® 350 Power Contact Extraction Tool

The auxiliary contacts used with wire sizes 16 to 24 AWG cannot be properly inserted without the insertion tool. Properly installed auxiliary contact of all wire gauges cannot be removed from the housing without the extraction tool.

All Data Subject to Change Without Notice 2024-0023 DS-SBEX160-175 REV 8 Your Best Connection™

2768 2118 F: +(86) 755 2768 2218 • www.ideal-Industries.in • www.andersonpower.com

Anderson™ will use reasonable efforts to include accurate and up-to-date content in the data sheet. All product information contained in the data sheet including ordering information, illustrations, specifications, and dimensions, are believed to be reliable as of the date of publishing, but is subject to change without notice. Anderson™ makes no warranty or representation as to its accuracy. Content in the data sheet may contain technical inaccuracies, typographical errors and may be changed or updated without notice. Anderson™ may also make improvements and/or changes to the products and/or to the programs described in the content at any time without notice. Current sales drawings and specifications are available upon request.

©2024 Anderson Power Products, Inc. All rights reserved. A®, Anderson Power Products®, SBE®, SBO®, SBS®, SBX®, PowerMod® and Powerpole® are registered trademarks of Anderson Power™ logo and Your Best Connection™ are trademarks of Anderson Power Products, Inc.



HEADQUARTERS: Anderson Power Products®, 13 Pratts Junction Road, Sterling, MA 01564-2305 USA T: +1 978-422-3800 F: +1 978-422-0128 • EUROPE: Anderson Power Products® Ltd., Unit 3, Europa Court, Europa Boulevard, Westbrook, Warrington, Cheshire, WA5 7TN United Kingdom T: +44 (0) 1925 428390 F: +44 (0) 1925 520203 • GERMANY: IDEAL® Industries Germany GmbH, Esslinger Strasse 7, D – 70771 Leinfelden-Echterdingen, T: +49 (0) 711 – 997606666 • ASIA / PACIFIC: IDEAL® Anderson Asia Pacific Ltd., Unit 922-928 Topsail Plaza, 11 On Sum Street, Shatin N.T., Hong Kong T: +(852) 2636 0836 F: +(852) 2635 9036 • INDIA: IDEAL® INDUSTRIES India Private Limited, 229-230, SPAZEDGE, Tower B, Sector 47, Sohna Road, Gurgaon – 122018, Haryana, India T: +(91) 956-0075905 T: +(91) 124-4495101 • CHINA: IDEAL® Anderson Technologies (Shenzhen) Ltd., Block A8 Tantou Western Industrial Park, Songgang Baoan District, Shenzhen, PR. China 518105 T: +(86) 755

^{*} TP0001 and TM0001 tools require locators to properly position contacts.

^{**} See Powerpole® family tooling chart for other Powerpole® contacts

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Anderson Power Products: